

# MIRANDA



An unusual six-fin design, the 3" diameter Miranda will turn heads at any launch site. Comes with our Kwik-Switch 2000 motor mount as standard equipment. Flies on G thru J power. Payload bay measures 12".



**Features Include:**

- Pre-slotted Quantum Tube airframe
- G-10 fiberglass fins
- "Kwik-Switch" motor mount for H through J motors
- Piston ejection system
- Multi-panel nylon parachute
- 12" Payload section with plastic nosecone
- Explicit instructions
- Decal sheet

**Dia.: 3.0" Height: 62" Weight: 52 oz. MMT: 54/38/29mm Kwik-Switch Chute size: 36" Launch lug: 3/8"**

## Recommended motors and predicted altitude chart

All motors shown are Aerotech. Information displayed as Altitude in Feet, Optimal Delay in Seconds

Re-load kit	G75J	H128W	H238T	H97J	H180W	H220T	I200W	
Miranda, 29KS		1057,6.97	1209,7.84		1735,8.94	1716,9.17	2952,11.15	
Single Use Motor	G80T	H55W	H70W					
Miranda, 29KS	683,5.56	1550,7.29	1576,7.81					
Re-load kit	H73J	H123W	H242T	H112J	I161W	I357T	I154J	I211W
Miranda, 38KS	1088,6.08	1597,7.88	1979,9.67	2443,9.54	2965,10.98	3085,11.84	3374,10.97	3975,12.50
	I300T	I195J	I284W	I435T	J350W			
	3967,12.84	3916,12.23	4884,13.87	4924,14.09	5854,14.76			
Re-load kit	J90W	J180T	J275W	J460T	J135W	K185W		
Miranda, 54KS	6415,12.08	6951,14.23	6612,15.04	6392,15.56	8617,14.47	9825,15.15		

Shaded cell means this motor/rocket combination requires absolutely top-notch construction to fly successfully.

Other motors can also be used but some may require modifications to the kit.

Always refer to the Motor Recommendations Chart at [www.publicmissiles.com](http://www.publicmissiles.com) for the latest information.